

Instalacja z trybu Live

Oficjalna Dokumentacja dla Mageia



Tekst oraz zrzuty ekranu są dostępne na licencji CC BY-SA 3.0 <http://creativecommons.org/licenses/by-sa/3.0/>.

Ten dokument został stworzony przy pomocy [Calenco CMS](http://www.calenco.com) [http://www.calenco.com] rozwijanego przez [NeoDoc](http://www.neodoc.biz) [http://www.neodoc.biz].

Dokumentacja została napisana przez wolontariuszy w ich wolnym czasie. Jeśli chcesz pomóc poprawić dokumentację skontaktuj się z [Zespołem Dokumentacji](https://wiki.mageia.org/en/Documentation_team) [https://wiki.mageia.org/en/Documentation_team],

Instalacja z trybu Live

Spis treści

Instalacja z trybu Live	1
1. Wybierz i użyj obrazu ISO	1
1.1. Wprowadzenie	1
1.2. Nośnik	1
1.3. Pobieranie i Sprawdzanie Mediów	3
1.4. Wypal lub zrzuć obraz ISO	3
2. Uruchom Mageia jako wersję Live	6
2.1. Uruchamianie medium	6
2.2. W trybie BIOS/CSM/Legacy	7
2.3. W trybie UEFI	8
3. Wybór języka	9
4. Licencja oraz informacje o wydaniu	9
4.1. Umowa Licencyjna	9
4.2. Informacje o Wydaniu	9
5. Konfiguruj strefę czasową	9
6. Clock Settings	9
7. Select Keyboard	10
8. Testowanie Magei w systemie Live	10
8.1. Tryb Live	10
9. Partitioning	10
9.1. Suggested Partitioning	10
9.2. Wybierz punkty montowania	12
9.3. Formatowanie twardego dysku	13
9.4. Custom Disk Partitioning with DiskDrake	13
9.5. Formatowanie	14
10. Zostaw lub usuń nieużywany materiał	14
11. Bootloader	15
11.1. Grub2	15
11.2. Bootloader Setup	15
11.3. Other Options	16
12. Uruchom ponownie	17
13. User Management	17
13.1. Ustawienie hasła administratora (root):	17
13.2. Dodaj użytkownika	18
14. Login Screen	18
15. Usuwanie Magei	18

Spis rysunków

1. EFI System Partition	13
2. BIOS boot partition	13

Ινσταλαχφα ζ τρυβυ Λιτωε



Nikt nie zobaczy wszystkich zrzutów ekranu zaprezentowanych w tym manualu. To które ekrany zobaczysz zależy od tego jaki posiadasz sprzęt oraz jakich wyborów dokonasz podczas instalacji.

1. Wybierz i użyj obrazu ISO

1.1. Wprowadzenie

Mageia is distributed via ISO images. This page will help you to choose which image best suits your needs.

There are three types of installation media:

- **Classical installer:** Booting with this media provides you with the maximum flexibility when choosing what to install, and for configuring your system. In particular, you have a choice of which Desktop environment to install.
- **LIVE media:** This option allows you to try out Mageia without having to actually install it, or make any changes to your computer. However, the Live media also includes an Installer, which can be started when booting the media, or after booting into the Live operating system itself.



The Live Installer is simpler compared to the Classical Installer - but you have fewer configuration options.



Live ISOs can only be used to create „clean” installations, they cannot be used to upgrade previously installed Mageia releases.

- **Net Install:** These are minimal ISO's containing no more than that which is needed to start the DrakX installer and find DrakX-installer-stage2 and other packages that are needed to continue and complete the install. These packages may be on the PC hard disk, on a local drive, on a local network or on the Internet.

These media are very light (less than 100 MB) and are convenient if bandwidth is too low to download a full DVD, or if you have a PC without a DVD drive or is unable to boot from a USB stick.

More details are given in the next sections.

1.2. Nośnik

1.2.1. Definicja

Here, a medium (plural: media) is an ISO image file that allows you to install and/or update Mageia and, by extension, any physical medium (DVD, USB stick, ...) the ISO file is copied to.

You can find Mageia ISO's [here](http://www.mageia.org/en/downloads/) [http://www.mageia.org/en/downloads/].

1.2.2. Klasyczne medium instalacji

1.2.2.1. Powszechne możliwości

- These ISOs use the Classical installer called DrakX
- They are used for performing clean installs or to upgrade a previously installed version of Mageia
- Different media for 32 and 64-bit architectures
- Some tools are available in the Installer „Welcome” screen: Ρεσχυε Συστημ, Μεμοριψ Τεστ, and Ηαρδωαρε Δετεχτιον Τοολ
- Each DVD contains many available desktop environments and languages
- You'll be given the choice during the installation to add non-free software

1.2.3. Nośniki live

1.2.3.1. Powszechne możliwości

- Can be used to preview the Mageia operating system without having to install it
- The Live media also includes an Installer.
- Each ISO contains only one desktop environment (Plasma, GNOME or Xfce)
- Different media for 32 and 64-bit architectures
- They contain non-free software

1.2.3.2. Live DVD Plasma

- Plasma desktop environment only
- All available languages are present
- 64-bit architecture only

1.2.3.3. Live DVD GNOME

- GNOME desktop environment only
- All available languages are present
- 64-bit architecture only

1.2.3.4. Live DVD Xfce

- Xfce desktop environment only
- All available languages are present
- 32 or 64-bit architectures

1.2.4. Net install media

1.2.4.1. Powszechne możliwości

- Different media for 32 and 64-bit architectures
- First steps are English language only

1.2.4.2. netinstall.iso

- Contains only free software, for those who prefer to not use non-free software

1.2.4.3. netinstall-nonfree.iso

- Contains non-free software (mostly drivers, codecs...) for those who need it

1.3. Pobieranie i Sprawdzanie Mediów

1.3.1. Pobieranie

Once you have chosen your ISO file, you can download it using either http or BitTorrent. In both cases, you are provided with some information, such as the mirror in use and an option to switch to an alternative if the bandwidth is too low.

If http is chosen you will also see some information regarding checksums.

md5sum, sha1sum and sha512sum (the most secure) are tools to check the ISO integrity. Copy one of the checksums (string of alphanumeric characters) for use in the next section.

In the meantime, a window to download the actual ISO will open:

Click on *Σαρε Φιλε*, then click OK.

1.3.2. Checking the integrity of the downloaded media

The checksums referred to earlier, are digital fingerprints generated by an algorithm from the file to be downloaded. You may compare the checksum of your downloaded ISO against that of the original source ISO. If the checksums do not match, it means that the actual data on the ISO's do not match, and if that is the case, then you should retry the download or attempt a repair using BitTorrent.

To generate the checksum for your downloaded ISO, open a console, (no need to be root), and:

- To use the md5sum, type: **md5sum path/to/the/image/file.iso**
- To use the sha1sum, type: **sha1sum path/to/the/image/file.iso**
- To use the sha512sum, type: **sha512sum path/to/the/image/file.iso**

Example:

```
[sam5@localhost ~]$ md5sum /home/sam5/Downloads/Mageia-4-RC-x86_64-DVD.iso
ec1ce42c4b003b5e9bea6911968195c8 /home/sam5/Downloads/Mageia-4-RC-x86_64-DVD.iso
[sam5@localhost ~]$ █
```

then compare the result (you may have to wait for a while) with the ISO checksum provided by Mageia.

1.4. Wypal lub zrzuć obraz ISO

The verified ISO can now be burned to a CD/DVD or „dumped” to a USB stick. This is not a standard copy operation, as a bootable medium will actually be created.

1.4.1. Wypalenie obrazu ISO na CD/DVD

Whichever software you use, ensure that the option to burn an *image* is used. Burn *data* or *files* is NOT correct. See the [the Mageia wiki](https://wiki.mageia.org/en/Writing_CD_and_DVD_images) [https://wiki.mageia.org/en/Writing_CD_and_DVD_images] for more information.

1.4.2. Zrzucić obraz ISO na pamięci USB

All Mageia ISOs are hybrids, which means you can dump them to a USB stick and then use that to boot and install the system.



Dumping an image onto a flash device destroys any previous file-system on the device and all existing data will be lost.



Also, the only partition on the flash device will then just be the Mageia ISO partition.

So, if an ISO of about 4GB is written to an 8GB USB stick, the stick will then only show up as 4GB. This is because the remaining 4GB is no longer formatted - hence not currently available for use. To recover the original capacity, you must reformat and repartition the USB stick.

1.4.2.1. Używanie graficznych narzędzi w Magei

You can use a graphical tool like [IsoDumper](https://wiki.mageia.org/en/IsoDumper_Writing_ISO_images_on_USB_sticks) [https://wiki.mageia.org/en/IsoDumper_Writing_ISO_images_on_USB_sticks]

1.4.2.2. Używanie graficznych narzędzi w Windows

Powinieneś spróbować:

- [Rufus](http://rufus.akeo.ie/?locale=en_US) [http://rufus.akeo.ie/?locale=en_US] using the "ISO image" option
- [Win32 Disk Imager](http://sourceforge.net/projects/win32diskimager) [http://sourceforge.net/projects/win32diskimager]

1.4.2.3. Using the Command line within a GNU/Linux system



It is potentially *dangerous* to do this by hand. You risk overwriting potentially valuable existing data if you specify the wrong target device.

1. Otwórz konsolę
2. Become a `root` (Administrator) user with the command `su -` (don't forget the `-`)

```
[sam5@localhost ~]$ su -  
Password:  
[root@localhost ~]#  
[root@localhost ~]#  
[root@localhost ~]# █
```


3. Plug in your USB stick - but do not mount it (this also means do not open any application or file manager that could access or read it)
4. Enter the command **fdisk -l**

```
[root@localhost ~]# fdisk -l

Disk /dev/sda: 298.1 GiB, 320072933376 bytes, 625142448 sectors
Units: sectors of 1 * 512 = 512 bytes
Sector size (logical/physical): 512 bytes / 4096 bytes
I/O size (minimum/optimal): 4096 bytes / 4096 bytes
Disklabel type: dos
Disk identifier: 0x000db4bf
Partition 3 does not start on physical sector boundary.

Device      Boot      Start          End      Blocks      Id System
/dev/sda1   *                2048     21256191    10627072    83 Linux
/dev/sda2                21256192     63528959    21136384    83 Linux
/dev/sda3                63530964     625137344   280803190+    5 Extended
/dev/sda5                63531008     84873215    10671104    83 Linux
/dev/sda6                84875264    127016959    21070848    83 Linux
/dev/sda7                127019008    135985151     4483072    82 Linux swap / Solaris
/dev/sda8                135987200    198598655    31305728    83 Linux
/dev/sda9                198600704    471588863   136494080    83 Linux
/dev/sda10               471590912    496777994    12593541+    83 Linux
/dev/sda11               496781312    504955079     4086884    82 Linux swap / Solaris
/dev/sda12               504958976    625137344    60089184+    83 Linux

Disk /dev/sdb: 7.5 GiB, 8011087872 bytes, 15646656 sectors
Units: sectors of 1 * 512 = 512 bytes
Sector size (logical/physical): 512 bytes / 512 bytes
I/O size (minimum/optimal): 512 bytes / 512 bytes
Disklabel type: dos
Disk identifier: 0x15005631

Device      Boot Start          End      Blocks      Id System
/dev/sdb1   *            1       7598079    3799039+    17 Hidden HPFS/NTFS

[root@localhost ~]# █
```

5. Find the device name for your USB stick (by its size), for example /dev/sdb in the screenshot above, is an 8GB USB stick.

Alternatively, you can find the device name with the command **dmesg**. Towards the end of the following example, you can see the device name starting with sd, and in this case, sdd is the actual device. You can also see that its size is 2GB:

```
[72594.604531] usb 1-1: new high-speed USB device number 27 using
xhci_hcd
[72594.770528] usb 1-1: New USB device found, idVendor=8564,
idProduct=1000
[72594.770533] usb 1-1: New USB device strings: Mfr=1, Product=2,
SerialNumber=3
[72594.770536] usb 1-1: Product: Mass Storage Device
[72594.770537] usb 1-1: Manufacturer: JetFlash
[72594.770539] usb 1-1: SerialNumber: 18MJTWLMPUCC3SSB
```

```
[72594.770713] usb 1-1: ep 0x81 - rounding interval to 128 microframes,
ep desc says 255 microframes
[72594.770719] usb 1-1: ep 0x2 - rounding interval to 128 microframes,
ep desc says 255 microframes
[72594.771122] usb-storage 1-1:1.0: USB Mass Storage device detected
[72594.772447] scsi host8: usb-storage 1-1:1.0
[72595.963238] scsi 8:0:0:0: Direct-Access      JetFlash Transcend 2GB
1100 PQ: 0 ANSI: 4
[72595.963626] sd 8:0:0:0: [sdd] 4194304 512-byte logical blocks: (2.14
GB/2.00 GiB)
[72595.964104] sd 8:0:0:0: [sdd] Write Protect is off
[72595.964108] sd 8:0:0:0: [sdd] Mode Sense: 43 00 00 00
[72595.965025] sd 8:0:0:0: [sdd] No Caching mode page found
[72595.965031] sd 8:0:0:0: [sdd] Assuming drive cache: write through
[72595.967251]   sdd: sdd1
[72595.969446] sd 8:0:0:0: [sdd] Attached SCSI removable disk
```

6. Enter the command: **dd if=path/to/the/ISO/file of=/dev/sdX bs=1M**

Where X=your device name eg: /dev/sdd

Example: `dd if=/home/user/Downloads/Mageia-6-x86_64-DVD.iso of=/dev/sdd bs=1M`



It might be helpful to know that **if** stands for **input file** and **of** stands for **output file**

7. Enter the command: **sync**
8. This is the end of the process, and you may now unplug your USB stick.

2. Uruchom Mageia jako wersję Live

2.1. Uruchamianie medium

You can boot directly from a Live DVD or USB. Usually, you just need to plug the USB device in or place the DVD in the drive and restart the computer.

If the computer does not automatically boot from the USB or DVD you may need to reconfigure your BIOS Boot Disk priority. Alternatively, you might try accessing the boot device menu to select a device from which the computer will boot.



To access the BIOS or boot menu when the computer is starting, you can try pressing either **F2**, **Del** or **Esc** for the BIOS, or **Esc**, **F8**, **F10** or **F11** for the boot device menu. These (fairly common) keys are just a selection of possible options though.



The actual screen that you will first see when booting from the Live media will depend on whether your computer motherboard is of the Legacy (BIOS) or UEFI type.

2.2. W trybie BIOS/CSM/Legacy



Pierwszy ekran podczas uruchamiania w trybie BIOS

Menu

- **Boot Mageia**

This option will boot the Mageia Live system from the connected DVD/USB media (expect a very slow system compared to an installed OS).

Once the boot is done, you can proceed to the installation.

- **+ use non-free video drivers (slower to boot)**

Boot the Mageia Live system using non-free video drivers

- **Install Mageia**

This option will install Mageia to a hard disk.

- **+ use non-free video drivers (slower to boot)**

Install Mageia using non-free video drivers

- **Memory Test**

Test the installed RAM by performing multiple read and write operations. Reboot to end the test.

- **F2 Language**

Press **F2** to have the installer use a specific language during the installation. Use the arrow keys to select the language then press **Enter**.

2.3. W trybie UEFI



First screen while booting in UEFI mode

Menu

- **Boot Mageia**

This option will boot the Mageia Live system from the connected DVD/USB media (expect a very slow system compared to an installed OS). Once the boot is done, you can proceed to the installation

- **Install Mageia**

This option will install Mageia to a hard disk.

- **F2 Language**

Press **F2** to have the installer use a specific language during the installation. Use the arrow keys to select the language then press **Enter**.



If you booted from a USB stick, you will see the above menu options duplicated, and in this case, you should choose from the menu pair that will be suffixed with "USB".

3. Wybór języka

- Select your preferred language. Mageia will use this selection during the installation and for your installed system.
- Mageia uses UTF-8 (Unicode) support by default. This may be disabled in the *Μυλτιπλε λαγγυαγες* screen if you know that it is inappropriate for your language. Disabling UTF-8 applies to all installed languages.
- You can change the language for your system post-installation in the Mageia Control Center # System # localization for your system.

4. Licencja oraz informacje o wydaniu

4.1. Umowa Licencyjna

- Before installing Mageia, please read the license terms and conditions carefully.
- These terms and conditions apply to the entire Mageia distribution and must be accepted before you can continue.
- To proceed, simply select *Αχχεπτ* and then click on *Νεξτ*

If you decide not to accept these conditions, then we thank you for your interest in Mageia. Clicking *Θυτ* will reboot your computer.

4.2. Informacje o Wydaniu

Important information about this particular Mageia release can be viewed by clicking on the *Ρελεασε Νοτεσ* button.

5. Konfiguruj strefę czasową

- Choose your timezone by choosing your country, or a city close to you in the same timezone.

In the next screen you can choose to set your hardware clock to local time or to GMT, also known as UTC.



Jeżeli posiadasz więcej niż jeden system operacyjny na swoim komputerze upewnij się, że wszystkie mają ustawiony czas lokalny, albo UTC/GMT.

6. Clock Settings

Here, you can select whether your computer internal clock is set to local time or UTC time.

In the *Αδωνυχεδ* tab, you can enable automatic time synchronization and specify an NTP server.

7. Select Keyboard

Here you can set the keyboard layout you wish to use with Mageia.

A suggested keyboard layout (highlighted), has been chosen for you based upon your previously selected language and timezone choices.

8. Testowanie Magei w systemie Live

8.1. Tryb Live

This is the screen you will see if you selected the **Boot Mageia** option from the Live media menu.

8.1.1. Testowanie sprzętu

One of the aims of using the Live mode is to test that your hardware is correctly managed by Mageia. You can check if all devices have a driver in the Hardware section of the Mageia Control Center:

- interfejs sieciowy: skonfiguruj za pomocą net_applet
- graphics card: if you see the previous screen, it's already OK.
- dźwięk: dzingiel został już odtworzony
- printer: configure your printer/s and print a test page
- skaner: skanuj dokument z...

If everything is satisfactory, you can proceed with the installation. If not, you can use the *Θυτε* button to exit.



The configuration settings you apply here are carried over if you decide to proceed with the installation.

8.1.2. Uruchom instalację

To launch the installation of the Live DVD to a hard disk or SSD drive, simply click the *Ινσταλλον Ηαρδ Δισκ* icon on the Live desktop. You will then see this screen, followed by the [Partitioning](#) step.

9. Partitioning

9.1. Suggested Partitioning

In this screen you can see the content of your hard drive(s) along with the DrakX partitioning proposals for where to install Mageia.

The actual options available from those shown below will vary according to the layout and content of your particular hard drive(s).

Main Options

- **Use Existing Partitions**

Jeśli dostępna jest ta opcja, oznacza to że zostały znalezione partycje linuxowe i mogą być użyte do instalacji.

- **Use Free Space**

Jeśli posiadasz nieużywane miejsce na dysku (niesformatowane), może być ono wykorzystane do instalacji Mageia.

- **Use Free Space on a Windows Partition**

If you have unused space on an existing Windows partition, the installer may offer to use it. This can be a useful way of making room for your new Mageia installation, but is a risky operation so you should make sure you have backed up all important files!

With this option, the installer displays the remaining Windows partition in light blue and the proposed Mageia partition in dark blue with their intended sizes just underneath. You have the option to modify these sizes by clicking and dragging the gap between both partitions. See the following screenshot:

- **Erase and use Entire Disk**

This option will allocate the entire drive for Mageia



This will erase ALL data on the selected hard drive. Take care! If you intend to use part of the disk for something else, or you already have data on the drive that you are not prepared to lose, then do not use this option.



Zauważ, że ta metoda spowoduje zmniejszenie rozmiaru partycji Windows. Partycja musi być "czysta", co oznacza, że Windows musi być poprawnie zamknięty za ostatnim razem gdy był używany. Musi być także zdefragmentowany, choć to nie daje pewności że wszystkie pliki zostały przesunięte poza obszar dysku, który zostanie użyty. Dlatego też bardzo wskazane jest zrobienie kopii zapasowej ważnych plików.

- **Custom Disk Partitioning**

Ta opcja daje Ci całkowitą kontrolę nad sposobem przeprowadzenia instalacji.

If you are not using the *Χυστομ δισκ παρτιτιονινγ* option, then the installer will allocate the available space according to the following rules:

- If the total available space is less than 50 GB, then only one partition is created. This will be the / (root) partition.
- If the total available space is greater than 50 GB, then three partitions are created
 - 6/19 of the total available place is allocated to / with a maximum of 50 GB
 - 1/19 is allocated to swap with a maximum of 4 GB
 - the rest (at least 12/19) is allocated to /home

This means that from 160 GB or greater available space, the installer will create three partitions:

- 50 GB for /
- 4 GB for swap
- and the remainder for /home



If you are using a UEFI system, the ESP (EFI System Partition) will be automatically detected - or created if it does not exist yet - and mounted on /boot/EFI. The *Χυστομ δισκ παρτιτιονινγ* option is the only one that allows to check it has been correctly done.

If you are using a Legacy (also known as BIOS) system with a GPT partitioned disk, you need to create a BIOS boot partition if it doesn't already exist. It should be about 1 MiB with no mount point. It can be created with the Installer, under *Χυστομ δισκ παρτιτιονινγ*, like any other partition. Be sure to select „BIOS boot partition” for filesystem type.

See [DiskDrake](#) for information on how to proceed.



Some newer drives are now using 4096 byte logical sectors, instead of the previous standard of 512. Due to lack of available hardware, the partitioning tool used in the installer has not been tested with such a drive.

Some SSD devices now use an erase block size over 1 MB. If you have such a device we suggest that you partition the drive in advance, using an alternative partitioning tool like gparted, and to use the following settings:

- *Αλιγν το* = MiB
- *Φρεε σπαχε πρεχεδινγ* (MiB) = 2

Also make sure all partitions are created using an even number of megabytes.

9.2. Wybierz punkty montowania

Here you see the Linux partitions that have been found on your computer. If you don't agree with the DrakX suggestions, you can change the mount points yourself.

- To the left of the drop-down menus is a list of available partitions. For example: sda is a hard drive - and 5 is a *παρτιτιον νυμβερ*, followed by the *(χαπαχιτιψ, μουντ ποιντ, φιλεσυστεμ τυπε)* of the partition.
- If you have several partitions, you can choose various different *μουντ ποιντς* from the drop down menu, such as /, /home and /var. You can even make your own mount points, for instance /video for a partition where you want to store your films, or perhaps /Data for all your data files.
- For any partitions that you don't need to make use of, you can leave the mount point field blank.



If you make any changes here, ensure you still have a / (root) partition.



If you are not sure what to choose, click *Προεπιουσ* to go back and then tick *Χυστομ δισκ παρτιτιονινγ*, where you can click on a partition to see its type and size.

If you are sure the mount points are correct, click on *Νεξτ*, and choose whether you only want to format the partition suggested by DrakX, or more.

9.3. Formatowanie twardego dysku

- Click on *Προεπιουσ* if you are at all unsure about your choice.
- Click on *Νεξτ* to proceed if you are sure that it is OK to erase **every** partition, **every** operating system and **all data** that might be on that hard disk.

9.4. Custom Disk Partitioning with DiskDrake

- Modify the layout of your disk(s) here. You can remove or create partitions, change the filesystem or size of a partition and even view their details before you start.
 - There is a tab at the top for every detected hard disk (or other storage device, like a USB key). In the screenshot above there are two available devices: *sda* and *sdb*.
 - For all other actions: click on the desired partition first. Then view it, or choose a filesystem and a mount point, resize it or wipe it. *Εξπερτ μοδε* provides more options such as to label (name) a partition, or to choose a partition type.
 - Continue until you have adjusted everything to your satisfaction, then click *Δονε* when you're ready.
-



1. Take care with the *Χλεαρ αλλ* option, use it only if you are sure you want to wipe all partitions on the selected storage device.
 2. If you wish to use encryption on your / partition you must ensure that you have a separate /boot partition. The encryption option for the /boot partition must NOT be set, otherwise your system will be unbootable.
-



- If you are installing Mageia on a UEFI system, check that an ESP (EFI System Partition) is present and correctly mounted on /boot/EFI. See Figure 1 below.
 - If you are installing Mageia on a Legacy/GPT system, check that a BIOS boot partition is present and of the correct type. See Figure 2 below.
-

Rysunek 1. EFI System Partition

Rysunek 2. BIOS boot partition

9.5. Formatowanie

Here you can choose which partition(s) you wish to format. Any data on partitions not marked for formatting will be preserved.

Usually, at least the partitions that DrakX selected need to be formatted.

Click on *Αδυναλχεδ* to choose the partitions you want to check for so-called *βαδ βλοχκσ*



If you're not sure you have made the right choice, you can click on *Πρεπιουσ*, again on *Πρεπιουσ* and then on *Χυστομ* to get back to the main screen, where you can choose to view details of your partitions.

When you are confident about the selections, click on *Νεξτ* to continue.

10. Zostaw lub usuń nieużywany materiał

In this step, the installer looks for unused locales packages and unused hardware packages and you are then given an opportunity to delete them.

If you do not foresee a case where your installation may need to run on different hardware, or that you might need additional localization files then you might wish to accept this proposal.

Clicking *Αδυναλχεδ* will list the unused hardware and localization files that will be removed if you proceed.



The next step is the copying of files to hard disk. This process should just take a little while to complete. When it is finishing you will briefly get a blank screen - this is normal.

11. Bootloader

11.1. Grub2

Grub2 on Legacy MBR/GPT systems

- GRUB2 (with or without graphical menu) will be used exclusively as the bootloader for a Legacy/MBR or Legacy/GPT system.
- By default, a new bootloader will be written into either the MBR (Master Boot Record) of your first hard drive or in the BIOS boot partition.

Grub2-efi on UEFI systems

- GRUB2-efi will be used exclusively as the bootloader for a UEFI system.
- By default, a new bootloader (Grub2-efi) will be written into the ESP (EFI System Partition).

If there are already UEFI-based operating systems installed on your computer (Windows 8 for example), the Mageia installer will detect the existing ESP created by Windows and add grub2-efi to it. If no ESP exists, then one will be created. Although it is possible to have several ESPs, only one is required, whatever the number of operating systems you have.

11.2. Bootloader Setup

11.2.1. Podstawowe opcje programu rozruchowego

- **Bootloader to use**

This feature is only available to Legacy MBR/BIOS systems. Users of UEFI systems will not see this option here.

- **Boot device**

Don't change this unless you really know what you are doing

- **Delay before booting the default image**

This text box lets you set a delay, in seconds, before the default operating system is started up.

- **Security**

This allows you to set a password for the bootloader. This means a username and password will be required when booting in order to select a booting entry or change settings. This is optional, and most people are not likely to have a need for it. The username is root and the password is the one chosen hereafter.

- **Password**

Choose a password for the bootloader (optional)

- **Password (again)**

Retype the password and DrakX will check that it matches with the one set above

Αδωανχεδ

- Εναβλε AXIII

ACPI (Advanced Configuration and Power Interface) is a standard for power management. It can save energy by stopping unused devices. Deselecting it could be useful if, for example, your computer does not support ACPI or if you think the ACPI implementation might cause some problems (for instance random reboots or system lockups).

- Εναβλε ΣΜΠ

This option enables/disables symmetric multiprocessing for multi-core processors

- Εναβλε ΑΠΙΧ

Enabling this gives the operating system access to the Advanced Programmable Interrupt Controller. APIC devices permit more complex priority models, and Advanced IRQ (Interrupt Request) management.

- Εναβλε Λοχαλ ΑΠΙΧ

Here you can set Local APIC, which manages all external interrupts for a specific processor in an SMP system

11.2.2. Bootloader Configuration

- **Default**

The operating system to be started up by default.

- **Append**

This option lets you pass information to the kernel or tell the kernel to give you more information as it boots.

- **Probe foreign OS**

If you already have other operating systems installed, Mageia attempts to add them to your new Mageia boot menu. If you don't want this behaviour, then untick the Probe Foreign OS option.

Αδωανχεδ

- ζιδεο μοδε

This sets the screen size and colour depth to be used by the boot menu. If you click the down-triangle you will be offered other size and colour depth options.

- Δο νοτ τουχη ΕΣΠ ορ ΜΒΡ

Select this option if you don't want a bootable Mageia, but would rather chain-load it from another OS. You will get a warning that the bootloader is missing. Click Ok if you are sure you understand the implications, and wish to proceed.

11.3. Other Options

11.3.1. Użyj istniejącego bootloader'a.

The exact procedure for adding Mageia to an existing bootloader is beyond the scope of this documentation. However in most cases it will involve running the relevant bootlo-

ader installation program, which should detect Mageia and automatically add an entry for it in the bootloader menu. See the documentation for the relevant operating system.

11.3.2. Installing Without a Bootloader

While you can opt to install Mageia without a bootloader (see section 2.1 Advanced), this is not recommended unless you absolutely know what you are doing, as without some form of bootloader your operating system will be unable to start.

11.3.3. Dodaj lub zmodyfikuj wpis Boot Menu

To do this you need to manually edit `/boot/grub2/custom.cfg` or use the software **grub-customizer** tool instead (available in the Mageia repositories).



For more information, see: https://wiki.mageia.org/en/Grub2-efi_and_Mageia

12. Uruchom ponownie

Once the bootloader has been installed, you will be prompted to halt your computer, remove the live DVD/USB stick and restart the computer.



Ensure that you follow these shut-down and restart instruction steps in the **same** order.

When you are ready, press Φινιση.

When you restart, you will see a succession of download progress bars. These indicate that the software media lists are being downloaded (see Σοφτωαρε Μαναγεμεντ).

13. User Management

13.1. Ustawienie hasła administratora (root):

It is advisable for all Mageia installations to set a superuser (Administrator) password, usually called the `root` password in Linux. As you type a password into the top box a shield will change from red-to-yellow-to-green depending on the strength of the password. A green shield shows you are using a strong password. You need to repeat the same password in the box underneath, to check that the first entry was not mistyped.



All passwords are case-sensitive. It is best to use a mixture of letters (upper and lower case), numbers and other characters in a password.

13.2. Dodaj użytkownika

Add a User here. A regular user has fewer privileges than the superuser (root), but enough to use the Internet, office applications or play games and anything else the average user might use a computer for.

- **Icon**

Click on this button if you want to change the user's icon

- **Real Name**

Insert the user's real name into this text box

- **Login Name**

Enter the user login name or let DrakX use a version of the user's real name. **The login name is case-sensitive.**

- **Password**

Type in the user password. There is a shield at the end of the text box that indicates the strength of the password. (See also [Notatka](#))

Password (again): Retype the user password. DrakX will check that you have not mistyped the password.



Any users added while installing Mageia, will have a home directory that is both read and write protected (umask=0027)

You can add any extra needed users in the Χονφιγυρατιον – Συμμερνη step during the install. Choose Υσερ μαναγεμεντ.

Ustawienia dostępu mogą być również zmienione po instalacji.

14. Login Screen

SDDM login screen

Finally, you will come to the desktop login screen.

Enter your user name and user password, and in a few seconds you will find yourself with a loaded KDE Plasma or GNOME desktop, depending on which live medium you used. You can now start using and enjoying your Mageia installation.

You can find further documentation in [the Mageia wiki](https://wiki.mageia.org/en/Main_Page) [https://wiki.mageia.org/en/Main_Page].

15. Usowanie Magei

If Mageia didn't convince you or you can't install it correctly - in short you want get rid of it - that is your right and Mageia also gives you the possibility to uninstall. This is not true for every operating system.

After backing up your data, reboot your Mageia installation DVD and select Πεσχυε σψσ-τεμ, then Πεστορε Ωινδοωσ βοοτ λοαδερ. At the next boot, you will only have Windows, with no option to choose your Mageia operating system.

In Windows, to recover the space used by Mageia partitions: click on Start # Control Panel # Administrative Tools # Computer Management # Storage # Disk Management. You will recognise a Mageia partition because they are labeled Unknown, and also by their size and place on the disk. Right-click on each of these partitions and select $\Delta\epsilon\lambda\epsilon\tau\epsilon$ to free up the space.

If you are using Windows XP, you can create a new partition and format it (FAT32 or NTFS). It will then get a partition letter.

If you have Vista or 7, you have one more possibility, you can extend the existing partition that is at the left of the freed space. There are other partitioning tools that can be used, such as **gparted**, available for both Windows and Linux. As always, when changing partitions, be very careful to back up anything important to you.